


Cross-Screen Management System

(KM0104)


User Manual

1. Software Configuration


1) Connect Keyboard-Mouse switch and Computer with USB to DB9 Adapter cable. (Serial port driver need to be installed on connected port for the first connection)



2) Open **Cross-Screen V1.5.0.1** in the U-disk, double click **Kinan Cross Screen** to install.




The following interface will be displayed:




Function	Get device configuration 	Get the configuration of the current device
	Send device configuration 	Send the sliding mode to current device
Setting	CrossDisplay switch on/off	Unlock Cross-display mode
	Mouse speed 	Set each channel's sliding rate
	Language	English

2. Get the configuration of the current device

Click **【Get device configuration】** or  , then a interface appears, please select **COM1-> OK**




Then Configuration details appear:



3. Custom Cross-display mode


1) Remove or add channel

Select Channel 1, click ">>" to add this channel, click "<<" to remove this channel (this channel cannot slide after removing).




2) Move channel to customize Cross-display mode (Each channel's position can be moved at will)

① Style 1(Loop Mode)




② Style 2



Note:
Switch from 1 to 2 (Switch from upper right corner to right)
Switch from 1 to 3 (Switch from lower right corner to right)


③Style 3



Note:
Switch from 1 to 2 (Switch from upper right corner to right)
Switch from 1 to 3 (Switch from middle to right)
Switch from 1 to 4 (Switch from lower right corner to right)

3) Add or reduce screens


① Right click on the **Channel 1** icon and the following image appears.



Click "Add Screen" to enter the PC multi-screen mode, as shown below




② Right click on the "Channel 1-" icon, click "Add Screen" and the following image appears.




Channel 1-1 indicates that channel 1 has successfully added one screen to the PC multi-screen mode.

③ According to the above steps, you can add up to 3 screens per channel.


④ Mouse -> Enhance pointer precision



This option **Mouse -> Enhance Pointer Precision** must be consistent with the current PC's mouse properties. **"Mouse Properties"-> "Pointer Options" -> "Enhance pointer precision"**.



4. Mouse Speed



5. Send device configuration

Send the custom mode to the KM0104.

